



Dynamic white wall-mount controller controls lighting fixtures, wireless control of DW lighting fixture. Fits in any standard US switch box. Includes all the outputs in the back of the controller.

**Operating voltage**  
3V DC battery

**Features**

- Switch & dimming control function, control range > 20M.
- Smooth transition between light levels.
- Separately operate dimming and color temperature functions.
- Able to control 1 zone with endless receivers. Each receiver can maximally be controlled by 8 remotes.
- Power, temperature color and dimming functions operated by push button after receivers are connected.

**Color parameters**

- Brightness
- Saturation
- Fading

**ORDERING CODE**

Model

DDW-MC

DDW - Dynamic white controller

*Interference may be caused if other devices are operating in close range of 869.5Mhz frequency.*

## RGBW-RC-R

Dynamic white receiver



The DDW receiver is easily paired with controller by the click of a button. Receiver can be reset to factory settings at any time.

Each receiver can store one static DW color, one color sequence, and one brightness setting for the white LED strip. Receivers assigned to the same scene within the same zone will have the same LED static color and color sequence.

**Operating voltage**  
12-36 VDC

**Power capacity**  
up to 96W at 24V

**Operating temperature range**  
from -4 °F to +122 °F in case

**ORDERING CODE**

Model

RGBW-RC-R

RGBW-RC-R: Dynamic white receiver