# LETO 44WALL MOUNT ASYMMETRIC CYLINDER



□ 3.74" [95mm] 5 1 5" [131mm]

#### **Features**

- Three output options available up to 1500 lumens.
- Nine driver selections available to cover wide range of applications.
- Five year warranty.

#### Finish Options

White	Mocha
Black	Charcoal
Silver	Cerulean
	Firebrick



### **Technical Information**

OUTPUT OPTIONS	700 lm	1000 lm	1500lm
ixture wattage	6.2 W	9.6 W	14.6 W
Delivered Lumen at 3500K	540 lm	824 lm	1281 lm
Efficacy	108 lm/W	110 lm/W	109 lm/W
Center Beam Candlepower	921 cd	1405 cd	2185 cd

сст		TM-30						
	Multiplier	CRI	Rf	Rg	R9			
2500K	0.81	92	90	104	77			
2700K	0.92	92	91	102	61			
3000к	0.97	95	92	102	61			
3500К	1.00	95	93	101	72			
4000K	1.07	95	92	103	68			
6500K	1.05	96	91	100	89			

# **Ordering Code**

Integral Driver Example: Fixture LET44-WM-S-07-25K-ASM-DL-WH-WH-PHSD-NA Remote Driver Example: Fixture LET44-WM-S-07-25K-ASM-DL-WH-WH-PHSD-NA-HRM-LET44-SW-07-25K-PHSD-NA

Fixture MODEL TYPE SIZE OUTPUT CCT OPTIC ACCESSORY **BODY FINISH BAFFLE FINISH** Standard Standard 25K - 2500K 27K - 2700K 30K - 3000K 35K - 3500K 40K - 4000K 07 - 700 (6.2W) 10 - 1000 (9.6W) 15 - 1500 (14.6W) WH - White BK - Black SL - Silver WH - White BK - Black SL - Silver **S** - Small<sup>1</sup> **M** - Medium LET44 - Leto 44 WM - Wall Mount ASM - Asymmetric DL - Diffusing Lens L - Large Premium<sup>2</sup> Premium<sup>2</sup> MA - Mocha CC - Charcoal CR - Cerulean FB - Firebrick MA - Mocha CC - Charcoal CR - Cerulean FB - Firebrick 65K-6500K DRIVER DRIVER OPTIONS<sup>6</sup>

NA - None EMG - Emergency Driver<sup>4,5</sup>

- PHSD Forward/Reverse Phase, 1% Dimming, 120V Only

   0105 0-10V, 1% Dimming, 120/277V

   0103 0-10V, 1% Dimming, 347V Only<sup>4</sup>

   0101 EdolED, 0-10V, Linear, 0.1% Dimming, 120/277V<sup>4</sup>

   010G EdolED, 0-10V, Log, 0.1% Dimming, 120/277V<sup>4</sup>

   DALI EdolED, DALI Protocol 2, DT-8, 0.1% Dimming, 120/277V<sup>4</sup>

   DALI EdolED, DALI Protocol 2, DT-8, 0.1% Dimming, 120/277V<sup>4</sup>

   UUTE Lutron Hilume Ecodigital, 1% Dimming, 120/277V<sup>3,4</sup>

   DMX EldolED, DMX, 0.1% Dimming, 120/277V<sup>4</sup>

Size Small max output is 1000 lumens.
 Premium finishes may have extended lead times. Custom RALs are available, please consult Inside Sales with specific request.
 IUTE driver is not available at 700 lumens.

4 - Drivers: 0103/010L/010G/DALI/DALI8/DMX/LUTE/EMG always require a remote driver.
 5 - Emergency option comes prewired from factory with driver in remote housing. 8W of continuous power provided for a minimum of 90 minutes. Must be installed within 30 feet of luminaire using 18 AWG wire. Not available with 0103, DMX, DALI8 or LUTE Driver.
 6 - AWNR/CSMB available upon request, contact Senso for details.

CONTACT FACTORY FOR MORE OPTIONS







#### Lens

**DL** Diffusing Lens



# **Remote Driver Housing**

Depending on the options selected in the order code on page 1, a Remote Driver Housing may be required. This will automatically be generated and put on your order as necessary.

REMOTE DRIVER	MODEL	OUTPUT	ССТ	DRIVER	DRIVER OPTIONS	Maxir	Maximum mounting distance to luminaire using 18 AWG wire					G wire		
-		-		-	]-	PHSD	0105	0103	010L	010G	DALI	DALI8	LUTE	DMX
HRM-Housing, Remote LET4	44-WM-Leto 44 Wall Mount	Same as Fixture	Same as Fixture	Same as Fixture	Same as Fixture	16'	16'	16'	72'	72'	72'	72'	15'	149'


#### 4" J-box

Minimum volume required to mount drivers in junction box: 70mm x 40mm x 30mm.







#### HRM Single with Externally Mounted Driver



#### HRM Double



#### EMG Emergency Driver






# **Standard Finish**



## **Premium Finish**


Two tone with Black Baffle Finish. Any combination may be used for baffle and body finishes.









TM-30






3000K





-----Reference Source ------ Test Source

#### 6500K



3500К





90°

809

0

## Photometry

